

TROUBLESHOOTING

- Inspect the following before diagnosing the system.
 - Faulty spark plug
 - Loose spark plug cap or spark plug wire connection
 - Water in the direct ignition coil (leaking ignition coil secondary voltage)
- If there is no spark at either cylinder, temporarily exchange the ignition coil with a known-good one and perform the spark test.
- If there is spark, the exchanged ignition coil is faulty.
- "Initial voltage" of the ignition primary coil is the battery voltage with the ignition switch ON and engine stop switch at RUN (The engine is not cranked by the starter motor).

	Unusual condition	Probable cause (Check in numerical order)
Ignition coil primary voltage	No initial voltage with ignition and engine stop switches ON. (Other electrical components are normal)	<ol style="list-style-type: none"> Faulty engine stop switch. An open circuit in Black/white wire between the ignition coil and engine stop switch. Loose or poor connect of the ignition coil primary wire terminal, or an open circuit in primary coil (Check at the ECM connector). Faulty ECM (when the initial voltage is normal while disconnecting ECM connector)
	Initial voltage is normal, but it drops down to 2 - 4 V while cranking the engine.	<ol style="list-style-type: none"> Incorrect peak voltage adaptor connections. Undercharged battery. No voltage between the Black/white (+) and Body ground (-) at the ECM multi-connector or loose ECM connection. An open circuit or loose connection in Green wire. An open circuit or loose connection in Blue/black and Yellow/blue wires between the ignition coils and ECM. Short circuit in ignition primary coil. Faulty side stand switch or neutral switch. An open circuit or loose connection in No.7 related circuit wires. <ul style="list-style-type: none"> Side stand switch line: Green/white wire Neutral switch line: Light green wire Faulty ignition pulse generator (measure the peak voltage). Faulty ECM (in case when above No. 1 - 9 are normal).
	Initial voltage is normal, but no peak voltage while cranking the engine.	<ol style="list-style-type: none"> Faulty peak voltage adaptor connections. Faulty peak voltage adaptor. Faulty ECM (in case when above No.1, 2 are normal).
	Initial voltage is normal, but peak voltage is lower than standard value.	<ol style="list-style-type: none"> The multimeter impedance is too low; below 10 MΩ/DCV. Cranking speed is too low (battery under-charged). The sampling timing of the tester and measured pulse were not synchronised (system is normal if measured voltage is over the standard voltage at least once). Faulty ECM (in case when above No. 1 - 3 are normal).
	Initial and peak voltage are normal, but does not spark.	<ol style="list-style-type: none"> Faulty spark plug or leaking ignition coil secondary current ampere. Faulty ignition coil (s).
Ignition pulse generator	Peak voltage is lower than standard value.	<ol style="list-style-type: none"> The multimeter impedance is too low; below 10 MΩ/DCV. Cranking speed is too low (battery under charged). The sampling timing of the tester and measured pulse were not synchronised (system is normal if measured voltage is over the standard voltage at least once). Faulty ECM (when above No. 1 - 3 are normal).
	No peak voltage.	<ol style="list-style-type: none"> Faulty peak voltage adaptor. Faulty ignition pulse generator.